



TELEDYNE
GAS AND FLAME DETECTION
Everywhereyoulook™

User Manual

SPYGLASS IR3-V

Flame Detector



Spyglass IR3-V

Flame Detector
USER MANUAL

User manuals in other languages are available on Website
<https://teledynegasandflamedetection.com>



Copyright © December 2025 by Teledyne gas and flame detection

All rights reserved. No reproduction of all or part of this document, in any form, is permitted without the written consent of Teledyne gas and flame detection

All of the information that is provided in this document is accurate to the best of our knowledge.

As a result of continuous research and development, the specifications of this product may be changed without prior notice.

Email: gasandflamedetection@Teledyne.com

Limitation of Liability

- The Company TELEDYNE GAS AND FLAME DETECTION, hereinafter referred to as Teledyne gas and flame detection throughout this document, shall not be held responsible for any damage to the equipment or for any physical injury or death resulting in whole or in part from the inappropriate use or installation of the equipment, non-compliance with any and all instructions, warnings, standards and/or regulations in force.
- No business, person or legal entity may assume responsibility on behalf of Teledyne gas and flame detection, even though they may be involved in the sale of Teledyne gas and flame detection products.
- Teledyne gas and flame detection shall not be responsible for any direct or indirect damage, or any direct or indirect consequence, resulting from the sale and use of any of its products **UNLESS SUCH PRODUCTS HAVE BEEN SELECTED BY Teledyne gas and flame detection ACCORDING TO THE APPLICATION.**

Ownership clauses

- The drawings, specifications, and information herein contain confidential information that is the property of Teledyne gas and flame detection.
- This information shall not, either in whole or in part, by physical, electronic, or any other means whatsoever, be reproduced, copied, divulged, translated, or used as the basis for the manufacture or sale of Teledyne gas and flame detection equipment, or for any other reason **without the prior consent of** Teledyne gas and flame detection.

Warning

- This is not a contractual document. In the best interest of its customers and with the aim of improving performance, Teledyne gas and flame detection reserves the right to alter the technical features of its equipment without prior notice.
- **READ THESE INSTRUCTIONS CAREFULLY BEFORE THE FIRST USAGE:** these instructions should be read by all persons who have or will have responsibility for the use, maintenance, or repair of the instrument.
- This instrument shall only be deemed to be in conformance with the published performance if used, maintained, and repaired in accordance with the instructions of Teledyne gas and flame detection by Teledyne gas and flame detection personnel or by personnel authorized by Teledyne gas and flame detection.

Important Information

- The modification of the material and the use of parts of an unspecified origin shall entail the cancellation of any form of warranty.
- The use of the unit has been projected for the applications specified in the technical characteristics. Exceeding the indicated values cannot in any case be authorized.

Warranty

- Under normal conditions of use and on return to the factory, SPYGLASS IR3-V carry a 5-year warranty, excluding accessories such as tilt mount, weather protection, etc.

Waste Electrical and Electronic Equipment (WEEE directive)



European Union (and EEA) only. This symbol indicates that, in conformity with directive DEEE (2002/96/CE) and according to local regulations, this product may not be discarded together with household waste.

It must be disposed of in a collection area that is set aside for this purpose, for example at a site that is officially designated for the recycling of electrical and electronic equipment (EEE) or a point of exchange for authorized products in the event of the acquisition of a new product of the same type as before.

Table of contents

1	General Information.....	1
1.1	User Manual	1
1.2	Symbols used	1
2	Introduction.....	3
2.1	Key Features.....	3
2.2	Model Number Description	4
2.3	Internal tests	4
2.4	Product Overview.....	5
2.5	Accessories.....	6
3	Installation	11
3.1	General Considerations	11
3.2	Preparations for Installation	13
3.3	Required Tools.....	14
3.4	Certification Instructions	14
3.5	Mounting the Tilt Mount	15
3.6	Mounting the detector.....	16
3.7	Electrical Wiring.....	17
3.8	Current Output (0-20mA) Wiring.....	19
3.9	4 Wire Relay Connection.....	20
3.10	RS-485 Communication Network	21
3.11	Cabling Recommendations.....	22
3.12	Earth/Ground Regime	22
4	Configuration options.....	25
4.1	Sensitivity	26
4.2	Ultra-Fast Detection	26
4.3	Alarm Delay	26
4.4	Alarm Latch	26

Spyglass IR3-V

Flame Detector
USER MANUAL

4.5	Enable Pre-Alarm 0-20mA.....	27
4.6	Enable dirty window warning 0-20mA.....	27
4.7	Auxiliary Relay	27
4.8	Window Heater.....	28
4.9	Video Settings.....	28
4.10	Modbus Address.....	28
4.11	Manual BIT – Alarm Output Test (Full loop test)	28
5	Operation.....	29
5.1	Output Signals.....	30
5.2	Testing	30
5.3	Flame Simulator	31
6	Maintenance	33
6.1	Cleaning Procedure	33
7	Troubleshooting	35
8	Servicing.....	37
9	Communicator Software.....	39
10	Specifications	41
10.1	Fire Detection.....	41
10.2	Video Functionality.....	41
10.3	Electrical Specifications	41
10.4	Outputs.....	42
10.5	Mechanical Specifications	43
10.6	Environmental Specifications	43
10.7	Product Labeling.....	44
10.8	Approvals.....	46
10.9	Electromagnetic Compatibility.....	47
11	Performance	49
11.1	SG50-F-IR3-V-ASX0, SG50-F-IR3-V-ASX1, SG50-F-IR3-V-ASX2	49
11.2	SG50-F-IR3-V-ASX3, SG50-F-IR3-V-4	51

11.3 SG50-F-IR3-V-ASX5 52

11.4 False Alarm Immunity 54

12 Ordering Information 55

13 Appendix A..... 57

List of Figures

Figure 1 : Front view of the Spyglass SG50-F-IR3-V.....	5
Figure 2 : Rear view of the Spyglass SG50-F-IR3-V.....	5
Figure 3 : Tilt Mount.....	6
Figure 4 : Weather Cover.....	6
Figure 5 : Pole Mount.....	7
Figure 6 : Air Shield.....	7
Figure 7 : Flame Simulator kit.....	8
Figure 8 : Flame Simulator front view.....	8
Figure 9 : Duct Mount SP-F- DMX-S02.....	9
Figure 10 : Duct Mount SP-F- DMW-S02.....	9
Figure 11 : - Horizontal field of view.....	12
Figure 12 : Vertical field of view.....	12
Figure 13 : Tilt Mount Base - Plate View.....	15
Figure 14 : Tilt mount base – Side View.....	15
Figure 15 : Detector on Tilt mount – Side view.....	16
Figure 16 : Terminal view.....	17
Figure 17 : Source 4-Wire scheme.....	19
Figure 18 : Sink 4-Wire scheme.....	19
Figure 19 : Source 3-Wire scheme.....	20
Figure 20 : Sink 3-Wire scheme.....	20
Figure 21 : 4 Wire relay connection.....	21
Figure 22 : RS-485 Networking	21

List of Tables

Table 1: Terminal Connections.....	18
Table 2 : Detector Configuration Options.....	25
Table 3 : Sensitivity Levels.....	26
table 4 : AUX. RELAY – NORMALLY OPEN.....	27
table 5 : AUX. RELAY – NORMALLY CLOSED.....	27
Table 6 : Output Signal.....	30
Table 7: Common Troubleshooting Suggestions.....	35
Table 15: Ordering Information.....	55

1 General Information



WARNING: ALL INDIVIDUALS WHO HAVE OR WILL HAVE RESPONSIBILITY FOR USING, MAINTAINING, OR SERVICING THIS PRODUCT MUST READ THIS ENTIRE MANUAL CAREFULLY. FAILURE TO USE THIS EQUIPMENT PROPERLY COULD RESULT IN SERIOUS INJURY OR DEATH.

1.1 User Manual

The instructions given in this manual must be read thoroughly before installation and start-up, particularly those concerning the points related to the safety of the end-user. This user manual must be made available to every person involved in the activation, use, maintenance, and repair of the unit.

The information, technical data, and diagrams contained in this manual are based on the information that is available at a given time. In case of doubt, contact Teledyne gas and flame detection for additional information.

The aim of this manual is to supply simple and accurate information to the user. Teledyne gas and flame detection cannot be held liable for any misinterpretations in the reading of this manual. In spite of our efforts to produce an error-free manual, it may nonetheless contain some unintentional technical inaccuracies.

In the client’s interest, Teledyne gas and flame detection reserves the right to modify the technical characteristics of its equipment to increase their performance without prior notice.







The present instructions and their content are the inalienable property of Teledyne gas and flame detection.

1.2 Symbols used

Icon	Significance
	This icon and text designate information of special note.
	This symbol indicates: Earth ground connection.

Spyglass IR3-V

Flame Detector
USER MANUAL

Icon	Significance
	This symbol denotes: Protective earth terminal. A cable of the adequate diameter must be connected to ground and to the terminal having this symbol.
	This symbol denotes: Attention! In the present mode of use, failure to adhere to the instructions preceded by this symbol can result in a risk of electric shock and/or death.
	This symbol indicates: Failure to follow instructions may result in damage to or incorrect operation of the device.
	European Union (and EEA) only. This symbol indicates that this product must not be discarded with household waste, as per the EEA directive (2002/96/EC) and your own national regulations. This product must be disposed of at a collection point that is reserved for this purpose, for example, an official site for the collection of electrical and electronic equipment (EEE) in view of their recycling, or a point of exchange for authorized products that is accessible when you acquire a new product of the same type.
	This icon and text indicate the possibility of electrostatic discharge (ESD) in a procedure that requires the reader to take the proper ESD precautions.
	Warning: This icon and text indicate a potentially hazardous situation, which, if not avoided, could result in death or injury

2 Introduction

The **Spyglass IR3-V** flame detector will detect fires and explosions extremely quickly allowing preventative action to be initiated rapidly to help minimize the consequences!

- Detection within 40 milliseconds of fireballs or explosions
- Standard fire is detected within 1.5s from 100 ft. (30m), 4.1s from 230 ft. (70m) and 9.0s from 262 ft. (80m).

The detector provides fast response, high performance and reliable detection of all types of hydrocarbon fires (visible and non-visible). The detector addresses slow growing fires as well as fast eruption of fire using improved triple IR (IR3) technology. It operates in all weather and light conditions with highest immunity to false alarms.

The detector operates in all weather and light conditions. The detector provides high-definition (HD) video output of the monitored area with clear imaging of a fire event and of personnel at distances up to 100 ft (30m) allowing rescuers to discover the exact situation before entering the hazardous area. It will automatically record a video of a fire event (1 min pre-alarm/up to 3 mins post-alarm).

In addition, the detector provides high-definition (HD) video output of the monitored area with clear imaging of a fire event and of personnel at distances up to 100 ft (30m). This allows the rescue team to be aware of the exact situation before entering the hazardous area. The detector automatically records video of fire event (1 minute pre- and up to 3 minutes post-alarm initiation). These features, along with the built-in event logger, provide additional means to study the cause and development of fire events.

As an option, the color HD camera can be replaced with a near IR camera if greater flame definition is needed :

2.1 Key Features

- **Extreme sensitivity** - up to 260ft (80m) for a 1 ft² (0.1m²) N-heptane pan fire.
- **1.5 second detection time** - for 1 ft² (0.1m²) N-heptane pan fire at up to 100 ft. (30m) distance.
- **Ultra-fast detection mode** - detection within 40 milliseconds for fireballs or explosions.
- **HD video** output with **Automatic HD video recording** of fire events. Data/Event logger: Alarms, faults and other relevant events are logged to non-volatile memory.
- **Option: Improved false alarm immunity** in high CO₂ applications, like aircraft hangars or helidecks.
- **Option: Improved speed of response** - (0.5s) for enclosed space protection, like automotive applications in compliance with NFPA 33 or printing presses and conveyors.

- **Built-in-Test (BIT)** - Automatic (and manual) self-test of window cleanliness and the overall operation of the detector.
- **Window heater** to avoid condensation and icing.
- **Tilt mounting bracket** for accurate detector positioning.

2.2 Model Number Description

Model No are defined as follows:

SG50 - F - IR3 - F - V - A S X X

0	Standard with RGB camera, no Hart and not SIL certified
1	Standard with RGB camera With HART
2	Like model 1 with Near IR camera
3	Like model 1, but recommended for Hangar, Helideck, Petroleum Loading Racks with RGB camera
4	Like model 3 with Near IR camera
5	Like model 1 but with a fast response mode that is designed for, but not limited to, automotive spray paint applications where compliance with 0.5s response (per NFPA 33) is needed. With RGB camera

1	M25
2	¾" NPT

2.2.1 Enhanced performance options

Option 3: Increased false alarm immunity in presence of hot CO₂. Recommended for Hangar, Helideck and Petroleum Loading Racks

Option 5: Design for, but not limited to, automotive spray paint applications where compliance with 0.5s response (per NFPA 33) is needed

2.3 Internal tests

During normal operation, the flame detector performs self-tests of its optics, electronics and software. These include a periodic BIT (Built-In-Test) in which the sensors and window cleanliness are tested. Any detected fault is indicated as shown in Table 4 (in section 5). During "Dirty Window" fault the detection sensitivity is significantly reduced, while "Fault" refers to critical faults which totally prevent flame detection

2.4 Product Overview



Figure 1 : Front view of the Spyglass SG50-F-IR3-V



Figure 2 : Rear view of the Spyglass SG50-F-IR3-V

2.5 Accessories

2.5.1 Mounting Bracket

The detector should be mounted using the stainless-steel tilt mount part number SP-F-TILTMOUNT-SS2. This allows the detector to be securely attached to a wall, pole or other solid surface using appropriate fixings. See section 3.5 and 3.6 for further details.



Figure 3 : Tilt Mount

2.5.2 Weather Cover

The weather cover P/N SP-F-WEATHERCOVER-2 protect the detector from extreme weather conditions such heat, rain and snow



Figure 4 : Weather Cover

2.5.3 Pole mount

The pole mount enables the detectors to be installed with its tilt mount brackets. The pole mount kit we supply are suitable for 2-inch or 3-inch poles. Part number Standard with RGB camera SP-F-POLEMOUNT-23.



Figure 5 : Pole Mount

2.5.4 Air shield

The air shield P/N SP-F-AIRSHIELD-2 allows installation of flame detectors in harsh weather conditions where they may be exposed to dust, sand, and other particulate matter. The connection point can be mounted in the 3, 9 or 12 o'clock locations.

- Air pressure source: Clean, dry, and oil-free air
- Pressure: 2-3 bar /30-45 psi
- Fitting: 7/16"–20UNF-2A
- Operation temperature: -55°C to +85°C / -67°F to +185°F



Figure 6 : Air Shield

2.5.5 Flame Simulator

The Spyglass IR3-V may be tested using the SP-F-SIM-IR3. The Spyglass flame simulator family provides a fast and convenient means of periodically testing the detector and control system end-to-end. Maintenance costs can be reduced as the detectors can be tested in situ without needing a hot work permit.



Figure 7 : Flame Simulator kit

Flame Simulators emit IR radiation which simulates a fire to the detectors. The simulators are lightweight, easy to use, with testing distances of up to 30 ft. (9m) and capable of more than 1000 activations between battery charging. Spyglass Flame Simulators are ATEX approved for use in hazardous Zone 1, Zone 2, Zone 21, Zone 22 areas.

Each simulator kit contains a carrying case, simulator, carrying strap, battery charger, user manual, Allen key and a tool for removing the simulator rear cover.



Figure 8 : Flame Simulator front view

2.5.6 Duct Mount

Duct Mount SP-F- DMX-S02

The SP-F-DMX-S02 allows a standard (non-HD) detector to be mounted remotely from a potential fire source by allowing the device to look through cut hole in the side of a duct. This duct mount must be use with air shield SP-F-AIRSHIELD-S02




Figure 9 : Duct Mount SP-F- DMX-S02

Duct Mount SP-F-DMW-S02

The SP-F-DMW-S02 allows a standard detector to be mounted remotely from a potential fire source by allowing the device to look through a special sapphire window. It must be acknowledged that the detector cannot tell if this window becomes dirty and so a maintenance routine must be established to check the optical contamination of this window. Please note, the frequency of cleaning needed will vary from installation to installation. It is highly recommended therefore that a means of access be designed into the installation, as close as practicable to the assembly, for inspection and cleaning purposes.




Figure 10 : Duct Mount SP-F- DMW-S02

Spyglass IR3-V

Flame Detector
USER MANUAL

THIS PAGE IS LEFT INTENTIONALLY BLANK

3 Installation

This chapter does not attempt to cover all of the standard practices and codes of installation. Rather, it emphasizes specific points of consideration and provides some general rules for qualified personnel. You must always observe special safety precautions.

3.1 General Considerations



This section includes important information

- To help obtain optimal performance, the detector should be aimed toward the center of the hazard or area to be monitored and protected ("detection zone") and have, to the extent that is required, an unobstructed view of the protected area. Whenever possible, the detector face should be tilted (aimed) down at an angle to prevent the accumulation of dust and dirt.
- Do not start an installation until the performance target, system configuration, installation location and coverage considerations have been defined by the responsible person.

To ensure optimal performance the following guidelines should be addressed:

Sensitivity

To determine the sensitivity level, the following issues should be considered:

- ⚠ The size of the fire to be detected at the determined distance.
- ⚠ The type of flammable fuel.
- ⚠ Potential sources of false alarms that may be present (e.g., naked flames, hot process).

Spacing and Location

Consider the following factors when determining the number of detectors and their locations in the protected area:

- ⚠ The size and shape of the protected area
- ⚠ The nature of the hazards, including materials stored or used and the protected objects
- ⚠ The sensitivity of the detectors
- ⚠ If there are any obstructed lines of sight
- ⚠ The field of view of the detectors (See Figure 11 and Figure 12)




Figure 11 : - Horizontal field of view




Figure 12 : Vertical field of view

Environment

- Environmental conditions including but not limited to dust, snow or rain can reduce the detectors sensitivity and require additional consideration.

Hot Work

- ⚠ Arc welding should not be performed within 12 ft. (3.5m) of the detector. It is recommended that the system be inhibited during welding operations in situations where the possibility of a false alarm cannot be tolerated.
- ⚠ Gas welding requires a system inhibit, since the gas torch is an actual fire.
- ⚠ Arc welding rods can contain organic binder materials in the flux that burn during the welding operation and are detectable by the device.
- ⚠ Welding rods with clay binders do not burn and should not be detected. However, a system inhibit is always recommended, since the material being welded may be contaminated with organic substances (paint, oil, etc.) that will burn and may be of the size that should be detected

3.2 Preparations for Installation

The installation must comply with national and local regulations and standards applicable to flame detectors (e.g., NFPA 72) and all local and common engineering practices. It is recommended to consult with the authority having jurisdiction.

Prior to installation:

- Make sure that you have all the components and tools required to complete the detector installation readily available before beginning installation. In cases where you cannot complete the installation in a single session, secure and seal the detectors and conduits before leaving site.
- Use color-coded conductors or suitable wire markings or labels for the wiring. You may use 14 to 17 AWG (1.0mm² to 2.5mm²) multi-strand wires for the site wiring. The selection of wire gauge should be based on the number of detectors used on the same line and the distance from the control unit, in compliance with specifications.
- Individually screen twisted pair cable is recommended for RS485 terminals.
- Use suitably rating wire for the application certification and temperatures.

3.3 Required Tools

The detector can be installed using the following tools:

Tool	Function
Hex. KEY 6 mm	Vertical alignment
Hex. KEY 10 mm	Horizontal alignment
Wrench 13 mm	Mounting the detector
Flat Screwdriver 6 mm	Ground screw connection
Flat screwdriver 3.5mm	Terminal connection

3.4 Certification Instructions



WARNING

- ⚠ Do not open the detector, even when isolated, when flammable atmosphere present.
- ⚠ The equipment may be used in hazardous areas with flammable gases and vapors with apparatus groups IIC, IIB and IIA and with temperature classes T1, T2, T3, T4 and T5. See details of the explosion proof approvals in section 10.7.
- ⚠ The equipment is certified for use in ambient temperatures in the range of -

T6 $T_a = -58^{\circ}\text{F} \leq T_a \leq +140^{\circ}\text{F}$ ($-50^{\circ}\text{C} \leq T_a \leq +60^{\circ}\text{C}$) or

T5 $T_a = -58^{\circ}\text{F} \leq T_a \leq +167^{\circ}\text{F}$ ($-50^{\circ}\text{C} \leq T_a \leq +75^{\circ}\text{C}$) or

T4 $T_a = -58^{\circ}\text{F} \leq T_a \leq +185^{\circ}\text{F}$ ($-50^{\circ}\text{C} \leq T_a \leq +85^{\circ}\text{C}$).

and should not be used in temperatures outside this range.

- ⚠ Installation shall be carried out in accordance with the applicable code of practice by suitably trained personnel.
- ⚠ Inspection and maintenance of this equipment shall be carried out by suitably trained personnel in accordance with the applicable code of practice.
- ⚠ If the equipment is likely to come into contact with corrosive and/or other harsh substances, consult with the relevant technical persons to take suitable precautions to prevent the detector from being adversely affected, thus ensuring that the type of protection is not compromised.
- ⚠ Harsh substances: For example, acidic liquids, gases, or solvents that may attack the windows, metals, seals or polymeric materials.
- ⚠ Suitable precautions: For example, regular checks as part of routine inspections or establishing from the material's data sheet that it is resistant to specific chemicals.

Specific conditions for use

- ⚠ The equipment is not intended to be repaired by the user. Repair of this equipment shall be carried out by the manufacturer in accordance with the applicable code of practice.
- ⚠ The flame paths are not intended for repair. Contact the manufacturer if the flame paths are damaged.
- ⚠ Consult the manufacturer for genuine replacement cover and housing to connection box fasteners. M6x1x18 Hexagonal Socket head fasteners with a minimum of ISO 4762 Grade A4 Class 80 are acceptable alternatives.
- ⚠ One suitably certified stopping plug is supplied with the detector.
- ⚠ The external earthing connection consists of cable lug with M5x10 stainless steel screw, the terminals is suitable for connection of a wire of maximum 2.5mm² / 14 AWG.
- ⚠ The internal terminals are suitable for connection of a wire equal to or greater than the power input wiring and at a minimum of 1mm² / 17AWG conductor.

3.5 Mounting the Tilt Mount

The tilt mount enables the detector to be rotated up to 45 degrees (horizontal/vertical) in all directions. The following installation instructions show how to use it to support the detector from below (the preferred method).

To install the tilt mount:

- a) Mount the tilt mount base (Figure 13) to a solid structure using four suitable fixings through the four 7mm (0.28") diameter holes. Four captive screws with spring washers are provided in the tilt mount.




Figure 13 : Tilt Mount Base - Plate View




Figure 14 : Tilt mount base – Side View

3.6 Mounting the detector

Use the following steps to connect the detector to the tilt mount, referring to Figure 13:

- a) Place the detector, with its cable/conduit entries pointing down, on the holding plate of the tilt mount (item 2, Figure 15).
- b) Secure the detector to the plate using the two hex screws and spring lock washers (items 3 and 4).
- c) Loosen the locking screws (Items 5 and 6, Figure 15) in such a way that enables you to rotate the detector.
- d) Point the detector towards the detection area and make certain that the view of the area is unobstructed.
- e) Secure the detector in that position by tightening the locking screws (Items 5 and 6) on the tilt mount. (Make sure the detector is pointing in the correct direction).

The detector is now correctly mounted, aligned and ready for electrical connection. Please refer to section 3.7 for wiring instructions, and section 4 for a description of the detector's configuration settings.






Figure 15 : Detector on Tilt mount – Side view

Item N°.	Item name
1	Tilt mount assembly
2	Holding plate
3,4	Mounting HEX screws M8 and lock washers
5	HEX socket locking screw M8
6	HEX socket locking screw M12

3.7 Electrical Wiring

WARNING

-  The sensor module in the front half of the detector contains no serviceable components and should never be opened. Opening will invalidate the warranty of the detector. The terminal compartment at the back is the only part of the housing that should be opened by the user.
-  The detector has 22 screw terminals as shown in the following figure and table:




Figure 16 : Terminal view

Table 1: Terminal Connections

Pin #	Function	Description
Ground	Ground (earth)	Connected to a screw on the housing exterior.
1	24 VDC (+)	Power supply (18-32 VDC)
2	24 VDC (-)	Power supply return (0V)
3	0-20mA+ (In)	This output is used for analog 0-20 mA current output
4	0-20mA- (out)	
5	Fault Relay	A SPST contact relay, that is energized (closed) when the detector is in normal operation and opens in case of fault.
6	Fault Relay COM	
7	Alarm Relay (NO)	A normally open SPST contact relay, that is open in normal operation, and closed when fire is detected. This relay can be configured to latch as described in section (3.4).
8	Alarm Relay COM	
9	Analog Video +	Composite (analog) video output
10	Analog Video -	
A1	Auxiliary Relay NO	A normally open SPST contact relay with B1, that is open in normal operation, and closed according to the configuration used.
11	24 VDC (+)	Power supply (18-32 VDC)
12	24 VDC (-)	Power supply return (0V)
13	Manual BIT activation	The manual BIT (built-in test) can be initiated by momentarily short circuiting this terminal and one of the "24 VDC (-)" terminals (2 or 12)". See 3.1.1 Manual BIT – Alarm Output Test for more details.
14	RS 485 (+)	
15	RS 485 (-)	RS-485 Modbus communication (used by the "FGD Communicator" software)
16	Ethernet TX+	
17	Ethernet TX-	Ethernet communication, used for digital video (with ONVIF profile S protocol)
18	Ethernet RX+	
19	Ethernet RX-	
20	Shield	This terminal should be left connected to the housing internal ground screw.
B1	Auxiliary Relay COM	See A1 terminal

3.8 Current Output (0-20mA) Wiring

The detector's 0-20mA current output can act as both a source or a sink transmitter and can be 3-wire or 4-wire connected.

The following drawing shows how to wire the detector to act as a current source isolated transmitter (4-wire connection):




Figure 17 : Source 4-Wire scheme

The following drawing shows how to wire the detector to act as a current sink isolated transmitter (4-wire connection):




Figure 18 : Sink 4-Wire scheme

The following drawing shows how to wire the detector to act as a current source non-isolated transmitter (3-wire connection):




Figure 19 : Source 3-Wire scheme

Note: Link between 3 and 11 to be wired on site

The following drawing shows how to wire the detector to act as a current sink non-isolated transmitter (3-wire connection):




Figure 20 : Sink 3-Wire scheme

Note: Link between 4 and 12 to be wired on site

3.9 4 Wire Relay Connection

This wiring option uses the fault and alarm relay and are connected to fire alarm panels. This connection allows to connect several detectors on 4 wires in a single loop. On the last detector there is a connected EOL resistor in the connection box. The value of the resistor depends on the control panel specification.

The number of detectors in a single loop depends on the control panels power supply capacity and length on wire width.

In fault condition, the fault relay will open the contact. The control panel will see an open loop and will report a fault.

In alarm condition, the alarm relay will close the contact and short the loop. With this configuration, the panel does not know which detector in the loop caused the alarm or fault. See figure below.




Figure 21 : 4 Wire relay connection

3.10 RS-485 Communication Network

Using the RS-485 network capability of the detector and communicator software, it is possible to connect up to 32 detectors in an addressable system with only 4 wires (2 for power and 2 for communication). Using repeaters, the number of detectors can be much larger (32 detectors for each repeater) up to 247 on the same 4 wires. Using the RS-485 network, it is possible to read each detector's status (fault, alarm) and to initiate a BIT to each detector individually.

The detector communicates via RS-485 with a Modbus RTU compatible protocol. For more details on the communication protocol, please see manual SG50FMOBDBUS




Figure 22 : RS-485 Networking

3.11 Cabling Recommendations

The cable used should be appropriate for the hazardous area classification and meet local, national and company regulations.

In order to comply with EMC regulations, the cable must be shielded, and the detector grounded.

The use of industrial grade, suitably armored field cable is recommended). When using HART® communications, there are some additional considerations. In particular, low capacitance cable should be used. Further detailed information can be found at the HART® Communication Foundation's website www.hartcomm.org.

For ethernet cabling, it is recommended to use at least CAT5 shielded.

For analog video cabling, 75 Ohm - analog video patch cable or shielded twisted pair.

3.12 Earth/Ground Regime

Any earthing regime employed must avoid earth loops. The following information is provided to assist with proper earthing of the detector.

- ⚠ There is an earthing point on the outside of the detector enclosure for connection to Electrical ground.

3.12.1 General recommendations

- In general, correctly engineered star earthing arrangements minimize earth current crosstalk and noise, improving the reliability and performance of instrumentation.
- The use of a single, screened / shielded cable for each field device ensures good screening / shielding and reduces crosstalk.

3.12.2 Field Cabling

- The entire length of the field cabling connected to a unit should be screened / shielded. The screen / shield should be connected to a low noise instrument earth at one end.
- The screens / shields of field cabling must not be connected in a manner that creates earth loops or that will result in the screens / shields carrying large currents from heavy plant or equipment.

3.12.3 Interference and noise

- Electrical equipment connected to the system should comply with applicable national or international EMC standards.
- Ideally, the 24 V supply reaching units should be free from large transients, fluctuations or high frequency noise.
- In order to reduce the likelihood of radio frequency interference affecting the operation of units it is recommended that neither units nor their cabling are installed in close proximity to the antennae of high-powered radio, radar or satellite communication equipment.

Spyglass IR3-V

Flame Detector
USER MANUAL

THIS PAGE IS LEFT INTENTIONALLY BLANK

4 Configuration options

Some functions of the detector can be configured using an RS-485 modem connected to a computer with the “communicator” software. For details of how to download the software please contact technical support via email at oldhamsimtronics-support@Teledyne.com or detcon-service@Teledyne.com.

These configuration options are listed in the following table along with their factory default values.

Table 2 : Detector Configuration Options

Function	Options	Default Setting
Sensitivity	Very low, Low, Medium, High, Extreme	Medium
Ultra-fast detection	Disabled, Enabled	Disabled
Alarm Delay	0, 5, 10, 20 or 30 seconds	0 seconds (no delay)
Alarm Latch	Disabled, Enabled	Disabled
Video module	Disabled, Enabled	Enabled
Video analog output	Disabled, NTSC, PAL	Disabled
Enable Pre-Alarm 0-20mA	Disabled, Enabled	Disabled
Enable dirty window warning 0- 20mA	Disabled, Enabled	Disabled
Aux. Relay	Alarm Pre-Alarm Dirty Window Warning	Alarm
Aux. relay contact mode	Normally Open, Normally Closed	Normally Open
Window Heater	Disabled, Enabled	Enabled
Modbus address	1 – 247	1
Manual BIT – Alarm Output Test	Disabled, Enabled	Disabled

4.1 Sensitivity

The detector can be configured to one of four sensitivity levels: low, medium, high and extreme. The following table lists for each sensitivity setting the maximum distance, in which a standard fire¹ would be reliably detected.

Table 3 : Sensitivity Levels

Sensitivity level	Detection distance in feet (meters)	Number of LED flashes on Startup ²
Low	16 (5)	1
Medium	49 (15)	2
High	75 (23)	3
Extreme	98 (30)	4

Further details about the response characteristics of the detector at the different sensitivity settings and fuel types can be found in section 11.

4.2 Ultra-Fast Detection

The ultra-fast detection feature allows detection of fireballs and explosions at 40 milliseconds. This feature can be disabled or enabled regardless of the alarm delay configuration.

4.3 Alarm Delay

When a fire is detected, the detector delays the execution of the alarm outputs up to the configured time period. After this time delay, the detector re-evaluates the situation. If a fire is still detected the alarm outputs are activated.

4.4 Alarm Latch

If alarm latch is enabled, the detector outputs will remain active even after a flame is no longer detected. To reset the detector outputs the detector must be power cycled or a manual BIT initiated.

¹ A standard fire is defined as a 1x1 ft² (0.1 m²) N-heptane pan fire, with maximum wind speed of 6.5 ft/s (2 m/s)

² The LED flashing that appears on startup indicates the sensitivity the detector is set to. (see section 5)

4.5 Enable Pre-Alarm 0-20mA

If the Pre-Alarm is enabled and Alarm Delay is greater than 0, The detector 0-20mA output will be 16mA and the red LED will blink in case of a fire condition.

4.6 Enable dirty window warning 0-20mA

If enabled, this feature assists predictive maintenance by indicating an alert when the BIT signal is reduced by 75% of the value needed to trigger a BIT fault failure. When activated, the milliampere output will drop to 3mA and the LED will remain steady green, it should be noted that a fire signal will override the dirty window warning. A process variable of optical contamination (BIT signal level) is accessible via HART and / or MODBUS. The value of the field ranges from 0 (clean) to 100% (BIT fault).

4.7 Auxiliary Relay

The Aux relay can be set to operate in parallel to the alarm relay, at pre-alarm level or on "dirty window warning.". The contact relay can be set to Normally Open mode or Normally Closed mode for all settings. When the detector is not powered, the auxiliary relay is open regardless of the configuration setting.

In order to comply with SIL2 (for relay use only) the Auxiliary relay must be connected in parallel to the alarm relay and be configured as alarm, Normally Open (default setting).

table 4 : AUX. RELAY – NORMALLY OPEN

Aux. relay function setting	Aux. relay behaviour (in Normally Open setting)
Alarm	Closed when fire is detected. Otherwise, open.
Pre alarm	Closed in pre-alarm or fire alarm. Otherwise, open.
Dirty Window Warning	Closed when the detector window is contaminated above the warning level. Otherwise, open.

table 5 : AUX. RELAY – NORMALLY CLOSED.

Aux. relay function setting	Aux. relay behaviour (in Normally Closed setting)
Alarm	Open when fire is detected. Otherwise, Closed.
Pre alarm	Open in pre-alarm or fire alarm. Otherwise, Closed.

Dirty Window Warning	Open when the detector window is contaminated above the warning level. Otherwise, open.
----------------------	---

4.8 Window Heater

The detector is equipped with a heater to prevent condensation and icing on the window. If enabled, the heater is operated automatically depending on temperature.

4.9 Video Settings

The detector is equipped with a video camera and processing module. If enabled (“Video module” setting) the detector provides video outputs and records flame alarm events. The events are recorded from 1 minute before the flame was detected to 1, 2 or 3 minutes after (depending on the “post alarm video recording duration” setting).

Digital video output is provided via ethernet and ONVIF Profile S protocol. Composite (analog) video output is provided in NTSC or PAL format, depending on the “Video analog output” setting

4.10 Modbus Address

The detector can communicate with the communicator software using a Modbus RTU compatible protocol on RS-485. This protocol allows for a network of detectors to be connected, each with a unique Modbus address. The address of the detector can be set to any value in the range 1–247.

4.11 Manual BIT – Alarm Output Test (Full loop test)

When enabled, the alarm outputs are activated when a Manual BIT is initiated. See section 5.2 for details.



WARNING

Make sure all fire extinguishing actions or alarms connected to the detector are DISABLED when the manual BIT is initiated and the “Manual BIT – Alarm Output Test” is enabled as the Manual BIT will set the 0-20mA terminal to 20mA and close the alarm relay and auxiliary relay if configured.

5 Operation

The Spyglass IR3-V is a triple-IR flame detector that includes a built-in high-definition video camera module. The video module automatically records video of alarm events and can provide live video of the detection zone to a screen in the control room.

On power up, the LED on the front of the detector flashes Yellow indicating the startup routine has begun. After approximately 30 seconds, if the startup is successful, the LED turns green, the 0-20mA output goes to 4mA and the fault relay is closed.

Detector configuration settings can be changed as described in section 3.7. To restart the detector, cycle the power.

5.1 Output Signals

The detector has the following output signals:

- Current output (0–20mA) with HART® 7
- Relays (Fault, Auxiliary and Alarm)
- Modbus RS-485
- Tri-color status LED

Table 6 : Output Signal

State	Output	State				LED
		0 – 20mA	Fault Relay (NC)	Alarm Relay (NO)	Aux Relay	
State	Startup	1mA	Open	Open	Section 4.7	Flashing Yellow
	Fault	1mA	Open	Open		Flashing Yellow
	BIT fault	2mA	Open	Open		Yellow
	Dirty Window	3mA ³	Closed	Open		Green
	Normal	4mA	Closed	Open		Green
	Pre Alarm	16mA ⁴	Closed ⁵	Open		Flashing red
	Fire Alarm	20mA	Closed ⁵	Closed		Red

5.2 Testing

The detector has a Built-In-Test (BIT) capability to ensure proper operation and to indicate when the windows are dirty. The BIT process runs automatically at startup and periodically during the operation of the detector. The BIT can also be initiated manually by connecting the “Manual BIT” terminal and the “24 VDC (-)” terminal for one second (see Table 1) or by using the communicator software (connected through RS-485).

In case of “Dirty Window” fault the detector may still detect flames but at a lower sensitivity.

³ 3mA when “Enable dirty window warning 0-20mA” enabled. 4mA when “Enable dirty window warning 0-20mA” disabled.

⁴ 16mA when “Enable Pre-Alarm 0-20mA” enabled. 4mA when “Enable Pre-Alarm 0-20mA” disabled.

⁵ Fault relay will be open in alarm or pre-alarm states, if there is a BIT (Dirty Window) fault.

When “Manual BIT – Alarm Output Test” feature is enabled (see section 4.1.1), a successful Manual BIT will activate the following alarm outputs for a few seconds:

1. The LED in the front of the detector will turn red.
2. The 0-20mA current output will be set to 20mA.
3. The alarm relay will close.

**WARNING**

Make sure all fire extinguishing actions or alarms connected to the detector are DISABLED, when the manual BIT is initiated and the “Manual BIT – Alarm Output Test” is enabled, as the manual BIT will set the 0-20mA terminal to 20mA and close the alarm relay.

5.3 Flame Simulator

Flame simulators are often used by industry to perform detector testing during installation and periodic end to end testing of a flame detector alarm system. Refer to the Spyglass Flame simulator manual SP-F-SIM for full instructions.

THIS PAGE IS LEFT INTENTIONALLY BLANK

6 Maintenance

After powering up, the detector should work maintenance free. Regular checks should be in the form of a physical inspection and to periodically ensure the optical surfaces are clean (windows and reflective mirror). It is also recommended to perform a function test annually or in line with local requirements, whichever is the sooner.



WARNING

The sensor module in the front half of the detector contains no serviceable components and should never be opened. The terminal compartment at the back is the only part of the housing that should be opened by the user. Any violation of these instructions will invalidate the warranty.

6.1 Cleaning Procedure

To clean the detector:

- a) Disconnect the power to the unit and disable/inhibit any extinguishing equipment that is connected to the unit.
- b) Use water and detergent to clean the detector windows and underside of the reflector. Rinse with a soft cloth, cotton swab, or tissue.
- c) Where dust, dirt or moisture accumulates on the window, first clean the window with a soft optical cloth and detergent, and then rinse with a clean soft cloth, cotton swab, or tissue. If contamination continues to be an issue consider using the air shield.

THIS PAGE IS LEFT INTENTIONALLY BLANK

7 Troubleshooting

Use the table below to help troubleshoot any detector operational issues.

Table 7: Common Troubleshooting Suggestions

Detector Status	Possible Cause	Corrective Action
LEDs Off Fault Relay is open Current output at 0mA	No power to the unit	<ul style="list-style-type: none"> • Check that the power is connected to the detector. • Check power polarity. • Check wiring in the detector.
Yellow LED constantly on Fault Relay is open Current output at 0mA – 1mA	Power problems	<ul style="list-style-type: none"> • Check the voltage between the “24VDC (+)” and “24VDC (-)” terminals to verify that it is in the allowed range (see section 10.3)
Yellow LED constantly on Fault Relay is open 0–20mA at 2mA	BIT (Dirty Window) Fault	<ul style="list-style-type: none"> • Clean detector window. • Restart the detector (by turning the power off and then back on).
Red LED constantly on Alarm Relay closed and current output is at 20mA	Detector is in alarm latch mode	Restart the detector (by turning the power off and then back on) or perform a manual BIT.
Alarm Relay closed and current output is at 20mA	Detector is exposed to a flame	<ul style="list-style-type: none"> • Check cause of alarm. • If caused by “friendly fire”, re-position the detector so that it is not affected by it.
Green LED constantly on Fault Relay closed. No analog Video.	<ul style="list-style-type: none"> • Analog Video is not configured properly • Wiring problem 	<ul style="list-style-type: none"> • Make sure the “Video Analog Output” setting is configured to NTSC or PAL (according to the CCTV system used). • Check video wiring and polarity.
Green LED constantly on Fault Relay closed. No digital Video (through ethernet)	Wiring or software problem	<ul style="list-style-type: none"> • Check wiring and polarity. • Check ONVIF Client software.

THIS PAGE IS LEFT INTENTIONALLY BLANK

8 Servicing

The detector contains no user serviceable parts. In the event the detector has been damaged or is deemed to not be working properly, it should be returned to the manufacturer for repair. For technical assistance and to request a returns authorization number contact technical support via email at oldhamsimtronics-support@Teledyne.com or detcon-service@Teledyne.com.

THIS PAGE IS LEFT INTENTIONALLY BLANK

9 Communicator Software

The Communicator software can be used to configure and monitor the Spyglass-IR3 flame detector. The software communicates using Modbus over an RS-485 port to the detector. Modbus commands enable the user to configure parameters and monitor the status of the detector. For details of how to download the software and be sent a copy of the manual please contact technical support via email at oldhamsimtronics-support@Teledyne.com or detcon-support@Teledyne.com.

Spyglass IR3-V

Flame Detector
USER MANUAL



THIS PAGE IS LEFT INTENTIONALLY BLANK

10 Specifications

10.1 Fire Detection

- Detection time and distance:
 - 40ms - for fast fire burst or explosion
 - 1.5s - for 1ft² (0.1m²) N-heptane pan fire at 100 ft (30m)
 - 4s - for 1ft² (0.1m²) N-heptane pan fire at 230 ft (70m)
- Field of view: 90° Horizontal, 75° Vertical
- Time Delay: 0-30 seconds (adjustable)
- Built-in test: Automatic and Manual

10.2 Video Functionality

- HD Video allowing clear imaging of fire and people at 100ft. (30m) distance.
- Video recording of alarm events 1 minute before and up to 3 minutes after the flame is detected.
- System integration protocol: ONVIF (Open Network Video Interface Forum) Profile S

10.3 Electrical Specifications

- Operating Voltage: 24 VDC nominal (18-32 VDC)
- Current Consumption:
 - Standby 180mA
 - Maximum 300mA all systems in operation (including window heater)
- Cable Entries: 2x conduit entries 3/4" NPT or M25, with one entry plugged with a suitably certified stopper.
- Wiring: 14-17AWG (1.0-2.5mm²)

10.4 Outputs

- Relays: Volt-free contacts rated 2A at 30 VDC
 - Alarm: Normally open
 - Auxiliary: State selectable
 - Fault⁶: Closed when detector is operating without fault
- 0-20mA current output:
 - 3 wire and 4 wire (isolated) configurations, both sink or source.
 - Max load: 500Ω at 18-32VDC.
 - Supports HART[®]7 communication
 - The following table lists the 0-20 mA output at different detector statuses:

Detector status	Output
Fault	0 mA or 1 mA ±10%
BIT Fault	2 mA ±10%
Dirty window warning	3 mA ±10%
Normal	4 mA ±10%
Pre-alarm	16 mA ±3%
Alarm	20 mA ±3%

- Tri-colour LED indication
- Modbus RTU compatible Protocol on RS-485
- Digital Video: IP network IEEE 802.3 10Base-t

⁶ The FAULT relay will normally be energized and the contact will be closed during normal operation of the detector. The contact will be open at fault condition or low voltage .

10.5 Mechanical Specifications






- Size: 7.87 x 5.12 x 5.12" (200x130x130mm)
- Weight:
 - Detector (Stainless Steel 316): 9.8 lbs. (4.4 kg)
 - Tilt mount (Stainless steel 316): 5.4 lbs. (2.4 kg)

10.6 Environmental Specifications






- Temperature Range:
 - Operating and storage -67°F to +185°F (-55°C to +85°C)
- Humidity: up to 99%, non-condensing
- Ingress Protection: IP66 & IP68 (2m, 24hr); NEMA 4X & 6P

10.7 Product Labeling

10.7.1 Ex db

P/N	<input type="text"/>	S/N	<input type="text"/>	Mfg. Date	<input type="text"/>
					
II 2 G D		2575	1725	EN 54-10 UKE1017	
ICQC 22 ATEX 0483 X	Ex db IIC T5 Gb and Ex tb IIIC T95°C Db -55°C≤Ta≤75°C Ex db IIC T4 Gb and Ex tb IIIC T105°C Db -55°C≤Ta≤85°C				
IECEx FMG22.0017X	Ex db IIC T5 Gb and Ex tb IIIC T95°C Db -50°C≤Ta≤75°C				
FM22UKEX0141X	Ex db IIC T4 Gb and Ex tb IIIC T105°C Db -50°C≤Ta≤85°C				
FM22CA0053X	Class I, Div. 1, Groups B, C,D; T4				
FM22US0073X	Class II/III, Div. 1, Groups E,F,G; T4 T4 Ta=-50°C≤Ta≤85°C or T5 Ta=-50°C≤Ta≤75°C				
					
Class I, Zone 1, AEx/Ex db IIC T5 Gb Zone 21, AEx/Ex tb IIIC T95°C Db -50°C≤Ta≤75°C or Class I, Zone 1, AEx/Ex db IIC T4 Gb Zone 21, AEx/Ex tb IIIC T105°C Db -50°C≤Ta≤85°C					
Type 4X/6P/IP66/IP68 (2m,24hr) Vin: 18-32 VDC I _{max} : 300mA Standby: 210mA					
 TELEDYNE GAS AND FLAME DETECTION 14880 Skinner Road, Cypress TX, 77429 USA					

10.7.2 Ex db eb

P/N	<input type="text"/>	S/N	<input type="text"/>	Mfg. Date	<input type="text"/>
					
II 2 G D		2575	1725	EN 54-10 UKE1017	
ICQC 22 ATEX 0483 X	Ex db eb IIC T5 Gb and Ex tb IIIC T95°C Db -55°C≤Ta≤75°C Ex db eb IIC T4 Gb and Ex tb IIIC T105°C Db -55°C≤Ta≤85°C				
IECEx FMG22.0017X	Ex db eb IIC T5 Gb and Ex tb IIIC T95°C Db -50°C≤Ta≤75°C				
FM22UKEX0141X	Ex db eb IIC T4 Gb and Ex tb IIIC T105°C Db -50°C≤Ta≤85°C				
FM22CA0053X	Class I, Div. 1, Groups B, C,D; T4				
FM22US0073X	Class II/III, Div. 1, Groups E,F,G; T4 T4 Ta=-50°C≤Ta≤85°C or T5 Ta=-50°C≤Ta≤75°C				
					
Class I, Zone 1, AEx/Ex db eb IIC T5 Gb Zone 21, AEx/Ex tb IIIC T95°C Db -50°C≤Ta≤75°C or Class I, Zone 1, AEx/Ex db eb IIC T4 Gb Zone 21, AEx/Ex tb IIIC T105°C Db -50°C≤Ta≤85°C					
Type 4X/6P/IP66/IP68 (2m,24hr) Vin: 18-32 VDC I _{max} : 300mA Standby: 210mA					
 TELEDYNE GAS AND FLAME DETECTION 14880 Skinner Road, Cypress TX, 77429 USA					

10.7.3 Warning Label

Warning / Attention

Read and understand instruction manual before operating. Do not open when an explosive atmosphere is present. Seal All Conduits within 18 inches. Do not open when energized.

Lire et comprendre le manuel d instruction avant l' utilisation. Ne pas ouvrir quand une atmosphère explosive est présente. Sceller tous les conduits pour les 18 pouces. De pas ouvrir lorsqu'il est sous tension.

10.8 Approvals

Note: All items are designed and tested to meet the relevant requirements.

- Explosion proof:
 - ATEX: II 2 G D
 - Ex db IIC T5 Gb or Ex db eb IIC T5 Gb and Ex tb IIIC T95°C Db -55°C<Ta<75°C
 - Ex db IIC T4 Gb or Ex db eb IIC T4 Gb and Ex tb IIIC T105°C Db -55°C<Ta<85°C
 - UKCA:
 - Ex db IIC T5 Gb or Ex db eb IIC T5 Gb and Ex tb IIIC T95°C Db -50°C<Ta<75°C
 - Ex db IIC T4 Gb or Ex db eb IIC T4 Gb and Ex tb IIIC T105°C Db -50°C<Ta<85°C
 - IECEx:
 - Ex db IIC T5 Gb or Ex db eb IIC T5 Gb and Ex tb IIIC T95°C Db -50°C≤Ta≤75°C
 - Ex db IIC T4 Gb or Ex db eb IIC T4 Gb and Ex tb IIIC T105°C Db -50°C≤Ta≤85°C
 - FM & FMC:
 - Class I, Div. 1, Groups B, C & D; T4 Ta = -50°C≤Ta≤85°C or T5 Ta = -50°C≤Ta≤75°C
 - Class II/III, Div. 1, Groups E, F, G; T4 Ta = -50°C≤Ta≤85°C or T5 Ta = -50°C≤Ta≤75°C
 - Class I, Zone 1, AEx/Ex db IIC T4 Gb or Class I, Zone 1, AEx/Ex db eb IIC T4 Gb T4 Ta = -50°C≤Ta≤85°C or T5 Ta = -50°C≤Ta≤75°C
 - and
 - Zone 21, AEx/Ex tb IIIC T95°C Db -50°C≤Ta≤75°C or
 - Zone 21, AEx/Ex tb IIIC T105°C Db -50°C≤Ta≤85°C
- Performance:
 - ANSI FM 3260
 - EN 54-10
- Functional safety: Certified as SIL 2 per IEC 61508.
- MED B&D issued by DNV GL:
 - Temperature Class D; Vibration Class A; EMC Class B and Humidity IP68
- California Fire Marshall
- EAC CU TR

10.9 Electromagnetic Compatibility

The detector fully complies with EMC directive 2014/30/EU and protected against interference caused by RFI and EMI. The cables to the detector must be shielded and the detector must be grounded in order to comply to the EMC directive.

THIS PAGE IS LEFT INTENTIONALLY BLANK

11 Performance

The following tables show test results of detection distances and times for different fire scenarios. Each table lists results for a different sensitivity setting. For liquid fires the size of fire refers to the size of the pan, filled with the fuel. For gas fires the length of the plume is listed.

11.1 SG50-F-IR3-V-ASX0, SG50-F-IR3-V-ASX1, SG50-F-IR3-V-ASX2

Extreme Sensitivity

Fuel	Size	Distance Feet (m)	Average Response Time (Seconds)
N-Heptane	1 x 1 ft	262 (80)	9.0
N-Heptane	1 x 1 ft	230 (70)	4.1
N-Heptane	1 x 1 ft	98 (30)	1.5
Gasoline	1 x 1 ft	230 (70)	3.6
Diesel	1 x 1 ft	164 (50)	2.9
Methanol	1 x 1 ft	131 (40)	4.1
Methanol	1 x 1 ft	59 (18)	3.9
Ethanol	1 x 1 ft	125 (38)	4.2
Isopropanol	1 x 1 ft	180 (55)	3.5
Polypropylene	1 x 1 ft	115 (35)	10.1
Paper	1 x 1 ft	79 (24)	0.9
Ethylene glycol	1 x 1 ft	115 (35)	4.0
Wood	1 x 1 ft	148 (45)	3.8
JP5	1 x 1 ft	164 (50)	5.8
Kerosene	1 x 1 ft	164 (50)	5.1
Methane	32" plume	148 (45)	3.3
LPG	32" plume	180 (55)	4.8
Syngas*	32" plume	98 (30)	3.3
Lithium battery	5 cells 1.7V 1.5Ah	62 (19)	3.4
Gasoline	2 x 2 ft	328 (100)	5.3
JP5	2 x 2 ft	295 (90)	9.2

High Sensitivity

Fuel	Size	Distance ft (m)	Average Response Time (Seconds)
N-Heptane	1 x 1 ft	197 (60)	3.2
Methanol	1 x 1 ft	125 (38)	5.5
JP5	1 x 1 ft	148 (45)	4.9
LPG	32" plume	148 (45)	2.9

Medium Sensitivity

Fuel	Size	Distance ft (m)	Average Response Time (Seconds)
N-Heptane	1 x 1 ft	98 (30)	2.2
Gasoline	1 x 1 ft	98 (30)	1.5
Diesel	1 x 1 ft	79 (24)	3.9
JP5	1 x 1 ft	79 (24)	1.9
Kerosene	1 x 1 ft	79 (24)	2.5
Methanol	1 x 1 ft	75 (23)	1.2
Ethanol	1 x 1 ft	75 (23)	1.6
Isopropanol	1 x 1 ft	75 (23)	1.0
Paper	1 x 1 ft	39 (12)	0.8
Polypropylene	1 x 1 ft	66 (20)	2.6
Ethylene glycol	1 x 1 ft	56 (17)	3.4
Wood	1 x 1 ft	75 (23)	2.1
Methane	32" plume	82 (25)	0.8
LPG	32" plume	98 (30)	1.4
Syngas*	32-in Plume	49 (15)	0.8
Lithium battery	5 cells 1.7V 1.5Ah	43 (13)	2.4

Low Sensitivity

Fuel	Size	Distance ft (m)	Average Response Time (Seconds)
N-Heptane	1 x 1 ft	49 (15)	1.2
Jet fuel	1 x 1 ft	39 (12)	8.8
Methanol	1 x 1 ft	39 (12)	1.2
LPG	32" plume	49 (15)	1.4

Very low Sensitivity

Fuel	Size	Distance ft (m)	Average Response Time (Seconds)
N-Heptane	1 x 1 ft	25 (7.5)	1.6
Gasoline	1 x 1 ft	25 (7.5)	1.8
Methanol	1 x 1 ft	18 (5.5)	1.1
JP5	1 x 1 ft	20 (6)	1.5
LPG	32" plume	25 (7.5)	1.8

11.2 SG50-F-IR3-V-ASX3, SG50-F-IR3-V-4

Extreme Sensitivity

Fuel	Size	Distance Feet (m)	Average Response Time (Seconds)
N-Heptane	1 x 1 ft	262 (80)	4.2
Gasoline	1 x 1 ft	230 (70)	3.2
Diesel	1 x 1 ft	164 (50)	3.6
Jet fuel	1 x 1 ft	164 (50)	3.6
Kerosene	1 x 1 ft	164 (50)	3.5
Polypropylene	1 x 1 ft	115 (35)	3.3
IPA	1 x 1 ft	180 (55)	2.5
Wood	1 x 1 ft	148 (45)	5.7
Lithium battery	5 cells 3,7V 1.5AH	49 (15)	4.9
Jet fuel	2 x 2 ft	262 (90)	9.2

High Sensitivity

Fuel	Size	Distance ft (m)	Average Response Time (Seconds)
N-Heptane	1 x 1 ft	197 (60)	3.7
JP5	1 x 1 ft	148 (45)	3.2

Medium Sensitivity

Fuel	Size	Distance ft (m)	Average Response Time (Seconds)
N-Heptane	1 x 1 ft	98 (30)	0.8
Gasoline	1 x 1 ft	98 (30)	1.0

Spyglass IR3-V

Flame Detector
USER MANUAL

Diesel	1 x 1 ft	82 (25)	2.4
Jet fuel	1 x 1 ft	82 (25)	1.4
Kerosene	1 x 1 ft	82 (25)	1.2
Polypropylene	1 x 1 ft	66 (20)	3.3
IPA	1 x 1 ft	75 (23)	1.2
Wood	1 x 1 ft	75 (23)	1.0
Lithium battery	5 cells 3,7V 1.5AH	33 (10)	3.7
Jet fuel	2 x 2 ft	148 (45)	3.2

Low Sensitivity

Fuel	Size	Distance ft (m)	Average Response Time (Seconds)
N-Heptane	1 x 1 ft	49 (15)	1.2
Jet fuel	1 x 1 ft	39 (12)	1.2

Very low Sensitivity

Fuel	Size	Distance ft (m)	Average Response Time (Seconds)
N-Heptane	1 x 1 ft	25 (7.5)	1.0
Jet fuel	1 x 1 ft	20 (6)	1.1

* Syngas mixture: 30% volume methane, 70% volume hydrogen

11.3 SG50-F-IR3-V-ASX5

Medium Sensitivity

Fuel	Size	Distance ft (m)	Average Response Time (Seconds)
N-Heptane	1 x 1 ft	98 (30)	0.2
Gasoline	1 x 1 ft	98 (30)	0.1
Diesel	1 x 1 ft	79 (24)	0.3
Kerosene	1 x 1 ft	79 (24)	0.3
Methanol	1 x 1 ft	59 (18)	0.3
Ethanol	1 x 1 ft	59 (18)	0.3
IPA	1 x 1 ft	79 (24)	0.3
Methane	32" plume	79 (24)	0.1
LPG	32" plume	98 (30)	0.4

Low Sensitivity

Fuel	Size	Distance ft (m)	Average Response Time (Seconds)
N-Heptane	1 x 1 ft	49 (15)	0.2
Methanol	1 x 1 ft	29 (9)	0.4
LPG	32" plume	49 (15)	0.4

Very low Sensitivity

Fuel	Size	Distance ft (m)	Average Response Time (Seconds)
N-Heptane	1 x 1 ft	25 (7.5)	0.2
Methanol	1 x 1 ft	15 (4.5)	0.4
LPG	32-in Plume	25 (7.5)	0.3

* Syngas mixture: 30% volume methane, 70% volume hydrogen

11.4 False Alarm Immunity

The following table shows test results of false alarm immunity for detectors configured to “Extreme” sensitivity. For each radiation source a distance is listed. This is the minimum tested distance, from which the detectors did not alarm when exposed to the radiation source (either modulated or non-modulated).

False Stimuli only at Extreme Sensitivity

False Alarm Source	Maximum Distance in ft (m)
Sunlight, Direct, Reflected	N.R.
Sunlight, Direct, reflected with water drops on sensors	N.R.
Incandescent frosted glass light, 300W	N.R.
Fluorescent, 70W (3x23.3W)	N.R.
Electric arc	N.R.
Arc welding	12 (3.5)
Radiation heater, 1850W	N.R.
Radiation heater, 1850W with water drops on sensors	N.R.
Quartz lamp (1000W) shielded	N.R.
Quartz lamp (500W) non-shielded	N.R.
Mercury vapor lamp 160Wx3	N.R.
Car Exhausts	N.R.
Projector led	N.R.
Solenoid bell	N.R.
Soldering iron	N.R.
Electric Drill	N.R.

N.R. – No response at any distance. The shortest test distance was 2ft (0.5m).

12 Ordering Information

Table 8: Ordering Information

Part Number	Description
Flame Detector	
SG50-F-IR3-V-AS11	Spyglass IR3-HD, ATEX, FMus, FMc and IECEx certified, 316SS, M25 entries with RGB camera
SG50-F-IR3-V-AS21	Spyglass IR3-HD, ATEX, FMus, FMc and IECEx certified, 316SS, 3/4"NPT entries with RGB camera
SG50-F-IR3-V-AS12	As Spyglass -IR3-HD-AS11 with Near IR camera instead of RGB camera
SG50-F-IR3-V-AS22	As Spyglass -IR3-HD-AS21 with Near IR camera instead of RGB camera
SG50-F-IR3-V-AS13	As Spyglass -IR3-HD-AS11 with Near IR camera instead of RGB camera
SG50-F-IR3-V-AS23	As Spyglass -IR3-HD-AS21 with Near IR camera instead of RGB camera
SG50-F-IR3-V-AS14	As Spyglass -IR3-HD-AS11 with Near IR camera instead of RGB camera
SG50-F-IR3-V-AS24	As Spyglass -IR3-HD-AS21 with Near IR camera instead of RGB camera
SG50-F-IR3-V-AS15	As Spyglass -IR3-HD-AS11 but with enhanced speed of response option
SG50-F-IR3-V-AS25	As Spyglass -IR3-HD-AS21 but with enhanced speed of response option
SG50-F-IR3-V-AS10	As Spyglass -IR3-HD-AS11 without Hart and without SIL certification
SG50-F-IR3-V-AS20	As Spyglass -IR3-HD-AS21 without Hart and without SIL certification
Detector Tilt Mount	
SP-F-TILTMOUNT-SS2	Spyglass Stainless Steel Tilt Mount
Flame Simulator Kit	
SP-F-SIM-IR3	IR3 Spyglass Flame Simulator Kit Including Carry Case, Simulator, Carrying Strap, Charger and Manual
Flame Simulator Spare Parts	
SP-F-SIM-CASE	Carrying Case
SP-F-SIM-STRAP	Carrying Strap
SP-F-SIM-TOOL	Cover Removal Tool

Spyglass IR3-V

Flame Detector
USER MANUAL

SP-F-SIM-ALLEN	Allen Key
SP-F-SIM-CHRGR	Power Supply and Charger
SP-F-SIM-BATT	Replacement Battery
Flame Detector Accessories	
SP-F-WEATHERCOVER-2	Weather Cover, Stainless Steel
SP-F-POLEMOUNT-23	Pole Mounting Adaptor, Stainless Steel, of 2- and 3-inch pipes
SP-F-AIRSHIELD-2	Air Shield
SP-F-DMX-SO2	Duct Mount Assembly, without window. Use with SP-F-AIRSHIELD-2 (Solde separately)
SP-F-DMW-SO2	Duct Mount Assembly, with sapphire window
Communications	
SP-F-USB-RS485	RS485 to USB Converter (for connection of detector RS485 output to PC/Laptop for use with Communicator Software)

13 Appendix A

HART 7 Communications

Highway Addressable Remote Transducer (HART®) establishes digital data communication over 4-20mA Current Loop cables. The HART protocol uses FSK modulation signals superimpose at low level on top of the 4-20mA current.

The HART implementation on the Spyglass IR3-V Flame Detector allows the Control Unit to monitor the status of the detector, settings of User Configuration and initiate field diagnostics.

The HART protocol implemented in this flame detector is corresponds to HART rev. 7.0. It supports HART Universal commands including Common Practice and Device Specific Commands. For more detail information see manual SG50FHART-MANUAL-EN

THIS PAGE IS LEFT INTENTIONALLY BLANK

THIS PAGE IS LEFT INTENTIONALLY BLANK



TELEDYNE

GAS AND FLAME DETECTION

Everywhereyoulook™



AMERICAS

4880 Skinner Rd
Cypress, TX 77429
USA
Tel.: +1-713-559-9200

EMEA

ZI Est, Rue Orfila, CS20417
62027 Arras cedex
France
Tel.: +33 (0) 3 21 60 80 80

ASIA PACIFIC

Room 04, 9th Floor, 275
Ruiping Road, Xuhui District,
Shanghai, China
TGFD_APAC@Teledyne.com

www.teledynegasandflamedetection.com



© 2025 Teledyne gas and flame detection. All right reserved.

SG50FIR3V-EN Revision 2.0 /December 2025